CABLINE[®]-UX II

The simulation of passing PLUG through hinge

Part No. Plug: 20531-0**T-#2

Technical Report

1

1	R23212	2023/05/10	K. Baba	R. Takei	H. Ikari
0	R21112	2021/02/22	R. Hatano	T. Tanigawa	H. Ikari
Rev.	ECN	Date	Prepared by	Checked by	Approved by



QKE-DFFDE09-02 Rev.9

1. Purpose

Confidential C

We report the simulation results of the minimum diameter of the hinge that can store the connector(CABLINE-UX II Plug) and cable.

- 2. Simulation conditions
 - Connector : CABLINE-UX II PLUG CABLE ASS'Y (20531-0**T-#2)
 - X The simulation was performed at 20531-0 ^{**} T-02 and −12 have the same result as -02.
 - •Number of pins : 50P, 40P, 34P, 30P
 - Cable : MICRO-COAX CABLE AWG#44,46 (See Table 1 for jacket diameter)
 - ×Each simulation is connected to all Pins.
 - Bonding : CABLINE-UX II recommend bonding cable outlets.

When bonding, be sure to bend the cable from the end of the bonding.

Table.1 Cable jacket(outer) diameter (mm)

	Impedance matching		
AVVG#	45ohm	50ohm	
44	0.24		
46	0.22	0.24	



The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

2

Document No.

IER-001-10265-01EN

3. Simulation result

The simulation results are shown in Table.2 and 3. \times See the next page for details.

Table.2 Minimum hinge inner diameter with bonding (mm)

Table.3 Minimum hinge inner diameter without bonding (mm)

	Size	AWG#44	AWG#46	
Cable	Impedance matching	45ohm	45ohm	50ohm
	Jacket diameter	0.24	0.22	0.24
	Connector 30P	4.06	4.03	4.06
Minimum hinge	Connector 34P	4.06	4.03	4.06
inner diameter	Connector 40P	4.06	4.03	4.06
	Connector 50P	4.06	4.03	4.06

	Size	AWG#44	AWG#46	
Cable	Impedance matching	45ohm	45ohm	50ohm
	Jacket diameter	0.24	0.22	0.24
	Connector 30P	2.61	2.58	2.61
Minimum hinge	Connector 34P	2.62	2.58	2.62
inner diameter	Connector 40P	2.66	2.59	2.66
	Connector 50P	2.78	2.65	2.78

The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

3

Document No.

IER-001-10265-01EN

- 3. Simulation result
 - 3.1 With bonding

Simulation results with AWG #44 (45ohm).



The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

4

Document No.

IER-001-10265-01EN

Cable bend

40-Jacket diameter

Cable bend

- 3. Simulation result
 - 3.1 With bonding

Simulation results with AWG #46 (450hm).



The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

5

Document No.

IER-001-10265-01EN

40-Jacket diameter

Cable bend

- 3. Simulation result
 - 3.1 With bonding

Simulation results with AWG #46 (50ohm).



The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

6

Confidential C

Document No.

IER-001-10265-01EN

Cable bend

40-Jacket diameter

Cable bend

3. Simulation result

Confidential C

3.2 Without bonding

Simulation results with AWG #44 (450hm).



The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

Document No. IER-001-10265-01EN

Cable bend

40-Jacket diameter Ø**0.24**

Cable bend R0.50

- 3. Simulation result
 - 3.2 Without bonding

Simulation results with AWG #46 (450hm).



The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

8

Document No. IER-001-10265-01EN

Cable bend

40-Jacket diameter

Cable bend

- 3. Simulation result
 - 3.2 Without bonding

Simulation results with AWG #46 (50ohm).



The simulation results presented in this report are not guaranteed. The diameter of the hinge that can be passed through may vary depending on the processing method of the harness and the type of cables used. Please use the results as a reference value. Furthermore, the utilization of bonding is recommended.

I-PEX

9

Document No. IER-001-10265-01EN

Cable bend

40-Jacket diameter Ø**0.24**

Cable bend

I-PEX