

CABLINE®-SS

The simulation of passing PLUG through hinge

Part No. Plug: 20380-#**T-##

Technical Report

1	R23209	2023/05/10	K. Baba	R. Takei	H. Ikari
0	R21109	2021/02/22	R. Hatano	T.Tanigawa	H. Ikari
Rev.	ECN	Date	Prepared by	Checked by	Approved by

1. Purpose

We report the simulation results of the minimum diameter of the hinge that can store the connector(CABLINE-SS Plug) and cable.

2. Simulation conditions

Connector: CABLINE-SS PLUG CABLE ASS'Y (20380-#**T-##)

•Number of pins: 50P, 40P, 35P, 32P, 30P, 20P, 14P, 10P

• Cable: MICRO-COAX CABLE AWG#40,42 (See Table.1 for jacket diameter)


*Each simulation is connected to all Pins.


•Bonding: CABLINE-SS recommend bonding cable outlets.

When bonding, be sure to bend the cable from the end of the bonding.

Table.1 Cable jacket(outer) diameter (mm)

AWG#	Impedance matchin		
AVVG#	45ohm	50ohm	
40	0.33	0.37	
42	0.29	0.33	





3. Simulation result

The simulation results are shown in Table.2 and 3.

★See the next page for details.

Table.2 Minimum hinge inner diameter with bonding (mm)

	Size	AWG#40		AWG#42	
Cable	Impedance matching	40ohm	50ohm	45ohm	50ohm
	Jacket diameter	0.33	0.37	0.29	0.33
	Connector 10P	5.42	5.46	5.37	5.42
	Connector 14P	5.42	5.46	5.37	5.42
	Connector 20P	5.42	5.46	5.37	5.42
Minimum hinge inner diameter	Connector 30P	5.42	5.46	5.37	5.42
	Connector 32P	5.42	5.46	5.37	5.42
	Connector 40P	5.42	5.46	5.37	5.42
	Connector 50P	5.42	5.46	5.37	5.42

Table.3 Minimum hinge inner diameter without bonding (mm)

	Size	AWG#40		AWG#42	
Cable	Impedance matching	40ohm	50ohm	45ohm	50ohm
	Jacket diameter	0.33	0.37	0.29	0.33
	Connector 10P	3.95	4.00	3.91	3.95
	Connector 14P	3.95	4.00	3.91	3.95
	Connector 20P	3.95	4.00	3.91	3.95
Minimum hinge inner diameter	Connector 30P	3.97	4.07	3.91	3.97
	Connector 32P	3.97	4.09	3.91	3.97
	Connector 40P	4.12	4.27	3.94	4.12
	Connector 50P	4.19	4.39	4.03	4.19

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #40 (50ohm).




Fig.1 AWG#40 (50ohm) 50P




Fig.3 AWG#40 (50ohm) 32P




Fig.2 AWG#40 (50ohm) 40P




Fig.4 AWG#40 (50ohm) 30P

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #40 (50ohm).




Fig.5 AWG#40 (50ohm) 20P




Fig.6 AWG#40 (50ohm) 14P




Fig.7 AWG#40 (50ohm) 10P

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #40 (45ohm).




Fig.8 AWG#40 (45ohm) 50P




Fig.10 AWG#40 (45ohm) 32P




Fig.9 AWG#40 (45ohm) 40P




Fig.11 AWG#40 (45ohm) 30P

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #40 (45ohm).




Fig.12 AWG#40 (45ohm) 20P




Fig.13 AWG#40 (45ohm) 14P




Fig.14 AWG#40 (45ohm) 10P

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #42 (50ohm).




Fig.15 AWG#42 (50ohm) 50P




Fig.17 AWG#42 (50ohm) 32P




Fig.16 AWG#42 (50ohm) 40P




Fig.18 AWG#42 (50ohm) 30P

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #42 (50ohm).




Fig.19 AWG#42 (50ohm) 20P




Fig.20 AWG#42 (50ohm) 14P




Fig.21 AWG#42 (50ohm) 10P

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #42 (45ohm).




Fig.22 AWG#42 (45ohm) 50P




Fig.24 AWG#42 (45ohm) 32P




Fig.23 AWG#42 (45ohm) 40P




Fig.25 AWG#42 (45ohm) 30P

- 3. Simulation result
 - 3.1 With bonding Simulation results with AWG #42 (45ohm).




Fig.26 AWG#42 (45ohm) 20P




Fig.27 AWG#42 (45ohm) 14P




Fig.28 AWG#45 (50ohm) 10P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #40 (50ohm).




Fig.29 AWG#40 (50ohm) 50P




Fig.31 AWG#40 (50ohm) 32P




Fig.30 AWG#40 (50ohm) 40P




Fig.32 AWG#40 (50ohm) 30P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #40 (50ohm).




Fig.33 AWG#40 (50ohm) 20P




Fig.34 AWG#40 (50ohm) 14P




Fig.35 AWG#40 (50ohm) 10P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #40 (45ohm).




Fig.36 AWG#40 (45ohm) 50P




Fig.38 AWG#40 (45ohm) 32P




Fig.37 AWG#40 (45ohm) 40P




Fig.39 AWG#40 (45ohm) 30P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #40 (45ohm).




Fig.40 AWG#40 (45ohm) 20P




Fig.41 AWG#40 (45ohm) 14P




Fig.42 AWG#40 (45ohm) 10P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #42 (50ohm).




Fig.43 AWG#42 (50ohm) 50P




Fig.45 AWG#42 (50ohm) 32P




Fig.44 AWG#42 (50ohm) 40P




Fig.46 AWG#42 (50ohm) 30P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #42 (50ohm).




Fig.47 AWG#42 (50ohm) 20P




Fig.48 AWG#42 (50ohm) 14P




Fig.49 AWG#42 (50ohm) 10P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #42 (45ohm).




Fig.50 AWG#42 (45ohm) 50P




Fig.52 AWG#42 (45ohm) 32P




Fig.51 AWG#42 (45ohm) 40P




Fig.53 AWG#42 (45ohm) 30P

- 3. Simulation result
 - 3.2 Without bonding Simulation results with AWG #42 (45ohm).




Fig.54 AWG#42 (45ohm) 20P




Fig.55 AWG#42 (45ohm) 14P




Fig.56 AWG#42 (45ohm) 10P

